

# Installing Ricoh Driver for Windows 10



# Items you need to know

- „ IP address of Printer (#1 on the following page)
- „ Options that are installed And Paper Sizes (#2 on the following page)
- „ To get all this information you can print a configuration page from the Copier.
  - ... Hit User Tools, Machine Features (if present)
  - ... Then Printer Features
  - ... Then Configuration Page

## Configuration Page

RICOH Aficio MP C3000

### System Reference

Unit Number L3785600595 Pages Printed 47062  
 Total Memory 1024 MB  
 Firmware Version Printer[1.12 / B7885601K], System[1.69 / B2385601V], Engine[V1.131:01 / B2385630L], LCDC[1.18 / B2381491A], NIB[5.17 / B2385605H]  
 Device Connection IEEE 802.11b  
 HDD: Font / Macro Download Free Space 509908 KB , Disk Capacity 510446 KB  
 Printer Language RPCS [3.3.22.3.4], PCL 5c [1.13], PCL XL [1.13], Adobe PostScript 3 [1.00], Adobe PDF [1.00]

### Connection Equipment

Consumption Status  
 Black Toner Remaining: [ ■■■■ ] Cyan Toner Remaining: [ ■■■■ ]  
 Magenta Toner Remaining: [ ■■■■ ] Yellow Toner Remaining: [ ■■■■ ]

### Paper Input

Tray Priority  
 Bypass Tray Tray 1  
 Tray 1 8 1/2 x 11 Plain Paper Tray Locked Duplex Unavailable  
 Tray 2 11 x 8 1/2 Plain Paper  
 11 x 17 Plain Paper

### Maintenance

4 Color Graphic Mode Photo Priority

### System

\*On \* Indicates a non-default setting.  
 Print Error Report \*On  
 Memory Overflow Do not Print  
 Hours to Delete 8  
 Days to Delete 3  
 Memory Usage Frame Priority  
 Copies 1  
 Reserved Job Waiting Time Short Wait  
 Sub Paper Size Off  
 Letterhead Setting Off  
 Edge to Edge Print Off  
 Tray Switching Off  
 Auto Continue Off  
 Auto Del. Temp. Print Jobs Off  
 Auto Del Stored Print Jobs On  
 Initial Print Job List \*List Per User ID  
 Duplex Off  
 Blank Page Print On  
 Printer Language Auto  
 Page Size 8 1/2 x 11  
 Bypass Tray Setting Priority \*Machine Settings  
 Default Printer Language PCL

### PCL Menu

Orientation Portrait Form Lines \*45  
 Font Source Resident Font Number 0  
 Point Size 12.00 Font Pitch 10.00  
 Symbol Set PC-8 Courier Font Regular  
 Extend A4 Width Off Append CR to LF Off  
 Resolution \*300 dpi

### PS Menu

Data Format TBCP Resolution 600 dpi (Fast)  
 Color Setting Super Fine Color Profile Auto

### PDF Menu

Resolution 600 dpi (Fast)  
 Color Profile Auto Color Setting Super Fine

### Host Interface

I/O Buffer 128 KB I/O Timeout 15 seconds  
 DHCP On  
 Sub-net Mask 255.255.000.000 (000.000.000.000)  
 IPv6 Stateless Autoconfig. Active IPv4 Address 192.168.002.184 (011.022.033.044)  
 IPv4 Active Gateway Address 192.168.001.013 (000.000.000.000)  
 NetWare \*Inactive Frame Type (NW) Auto  
 AppleTalk Active IPv6 Inactive  
 LAN Type Ethernet SMB Active  
 Selected SSID MetroSales Ethernet Speed Auto Select  
 Transmission Speed Auto Communication Mode \*Infrastructure  
 WPA Encryption Method TKIP Channel 11  
 Security Type Off  
 WPA Authentication Method WPA-PSK

### Interface Information

MAC Address 00.00.74.ee.3e.e1 Host Name RNPAE3EE1  
 Operation Mode (NetWare) Print Server RNPAE3EE1  
 File Server Name (NetWare) Not Defined NDS Context Name (NetWare) Not Defined  
 Workgroups Name (SMB) WORKGROUP Network Path Name (SMB) \\RNPAE3EE1\MP\_C3000  
 IEEE 802.11b 00.00.74.b8.62.35  
 Invalid Interface Not Detected

2

1



# Software you need

Drivers for the machine can be  
downloaded from Ricoh's Website:  
.. <http://www.ricoh-usa.com>

Enter the numeric model number in the search box.

Choose a PCL 6 for universal driver unless you know that you need a Postscript driver.

When you Download drivers from the web, you must run the downloaded file to extract the


driver for use. Remember to save this file in a spot you can find it later.




# Next Start the Add Printer Wizard

- „ Hold the Windows key and press the "x" key.
- „ Then select Control Panel
- „ Then select View devices and printers
- „ Then select Add a printer at the top of the screen

On the following slides follow the notes on the side bar,  
Or select the buttons that are in the red boxes.



Now select, "The printer that I want isn't listed".



Now select, "Add a printer using a TCP/IP address or hostname".



← 

Type a printer hostname or IP address

Device type: TCP/IP Device

Hostname or IP address:

Port name:

Query the printer and automatically select the driver to use

Next Cancel

In the Hostname or IP address field, type in the IPv4 address from the Configuration Page (#1).

The Port name field will automatically fill in.

Be sure the “Query the printer” box is unchecked.

Then select next.



Install the printer driver

Choose your printer from the list. Click Windows Update to see more models.  
To install the driver from an installation CD, click Have Disk.


Manufacturer	Printers
Brother	Brother Color Leg Type1 Class Driver
Canon	Brother Color Type3 Class Driver
Dell	Brother Color Type4 Class Driver
Eastman Kodak Company	Brother Generic Jpeg Type1 Class Driver
EPSON	Brother Generic Jpeg Type3 Class Driver

This driver is digitally signed. [Tell me why driver signing is important](#)

Windows Update    Have Disk...


Next    Cancel

< Click on Have Disk...




< Click on Browse....


Now Browse to the folder you saved your print driver that you downloaded earlier.



Now Browse to the location where you saved your downloaded Ricoh driver, select it and Hit the Open button.



< Click on OK



Choose the PCL6 Driver for Universal Print.

< The Click "Next".

A screenshot of a Windows printer installation wizard window. The window has a light blue title bar with a close button (X) in the top right corner. Below the title bar is a black navigation bar containing a back arrow and a printer icon. The main content area is white and contains the following text: "Type a printer name" in blue, "Printer name:" followed by a text input field containing "Ricoh Printer", and "This printer will be installed with the PCL6 Driver for Universal Print driver." At the bottom right of the window, there are two buttons: "Next" (highlighted with a blue border) and "Cancel".

Now name your printer whatever you would like it to say and click "Next".



Printer Sharing

If you want to share this printer, you must provide a share name. You can use the suggested name or type a new one. The share name will be visible to other network users.

Do not share this printer

Share this printer so that others on your network can find and use it

Share name:


Location:

Comment:

Next Cancel

Select “Do not share this printer”.


Then click “Next”.




Now you can choose if you wish to make this printer your default printer.

You can also choose if you would like to print a test page.

When you are finished, you can click on "Finish".




Right click on the printer you just installed and select Printer Properties.



Your screen should look like this.

Select the "Advanced" tab.

Select "Printing Defaults..."





Here you can set the defaults for your print driver.

Set “2 sided” to off.

Set “Color/Black and White” to Black and White.

Hit Apply.

Hit OK.



Now select the “Ports” tab. Select “Configure Port...”.

Now Uncheck “SNMP Status Enabled”

Select “OK” on both screens.



You have now installed your printer😊